FCM8 - Fiber & Copper Panel


Fibernet's fiber & copper modular solution (FCM8) is a modular solution based on an eight module patch panel in standard 1U 19" racks.

The solution supports both fiber optics and copper modules, the Fiber & Copper modules enable users to an easy and tool less installation.

Make the installation easier by pre-terminated modules with trunks cables, Fiber optics or copper.

FCM8 - Installer Friendly

- Easy installation, includes all required parts and accessories
- · High performance results
- · Versatile high-density solution with compact, space-saving design
- Quick & Simple loading and/or removal of modules front and back







Copper Module



FCM8 - Fiber & Copper Panel

Modules Type

Fiber Optic Modules

The pre-terminated modules enable rapid deployment and are designed to provide quick and easy installation.

The trunk cables are available in sizes of 12, 24, 48 cable construction with SM or OM3/4 fibers.



Copper Modules

Fibernet pre-terminated trunk cables designed to improve efficiency and reduce labor cost.

Copper trunk cable assemblies with FCM8 modules are ideal solution for data center.

Trunk cables are available in sizes of 6, 12 and 24 in IDC Wire Gauge: 22~24 AWG, CAT6A, CAT7, CAT7A cable construction standards.



PRODUCT INFORMATION

Parameter	Panel Mechanical Properties				
Dimensions	465mm x 43.65mm x 70.29mm				
Adapter Compatibility	Optics-LC/SC; Copper-CAT6/6a				
Number input cable	8				
Maximum capacity (Fibers)	rs) Up to 96 LC fibers or 48 copper ports				
Working temperature	-10 °C to +60 °C (+14 °F to +140 °F)				
Relative Humidity	Up to 95%, non-condensing				
Storage Temperature	-40 °C to +70 °C (-40 °F to +158 °F)				
Patch Panel Material	Metal				
Standards Compliance	Copper solution is compatible with ISO/IEC 11801 & ANSI/TIA-568-C.2 CAT6/6A component level performance. Fiber solution meets ISO/IEC 11801 & ANSI/TIA-568-C.3 standards				
Color	Silver				

ORDERING INFORMATION

Patch-Panel

P/N - FCM8-1U



FCM8 Fiber Optics Modules - How to Order:

FCM8 - S G





Co	nnector Type	Fiber Type		No	No. of Fibers		Polish Type	
S	SC	0	OM3 B.I	6	6 Fibers (SC)	U	UPC	
L	LC	G	OM4 B.I	12	12 Fibers (LC)	Α	APC	
		7	OM4 B.I					

Copper Modules - How to Order:

FCM8 - C6 L

Cabl	е Туре	Туре		
C6	CAT6	U	UTP	
СбА	CAT6A	F	FTP	

For more information, please contact us at sales@fibernet.co.il